



GROUND FAULT DELAY BANDS:
 0.10-0.20-0.30-0.40sec.
 I^2t ON/OFF

- GROUND FAULT PICK-UP SETTINGS:
- 5000A --- 0.10-0.24x (0.01 INCREMENTS)
 - 4200A --- 0.10-0.28x (0.01 INCREMENTS)
 - 4000A --- 0.10-0.30x (0.01 INCREMENTS)
 - 3200A --- 0.10-0.37x (0.01 INCREMENTS)
 - 3000A --- 0.10-0.40x (0.01 INCREMENTS)
 - 2500A --- 0.10-0.48x (0.01 INCREMENTS)
 - 2000A --- 0.10-0.60x (0.01 INCREMENTS)
 - 1600A --- 0.10-0.75x (0.01 INCREMENTS)
 - 1200A --- 0.10-1.00x (0.05 INCREMENTS)
 - 800A --- 0.10-1.50x (0.05 INCREMENTS)
 - 600A --- 0.10-2.00x (0.05 INCREMENTS)
 - 225A --- 0.10-2.00x (0.05 INCREMENTS)

MULTIPLES OF CURRENT SENSOR (X)



SATIN AMERICAN CORP.
 40 OLIVER TERR.
 SHELTON CT, 06484
 P.O. BOX 619 1800-272-7711

Curves apply at 50/60 Hertz
 From - 20°C to + 65°C Programmer Ambient

LOW-VOLTAGE POWER CIRCUIT BREAKERS
etc. 11d/21d/31d Solid State Retrofit Tripping System
 Ground Fault Time-current Curves

DRAWING NO.
001-600-0006